Techmaster

User Manual

T9530

Display

Programm key

Foil keypad

Confirm key

OPENING USER

Press any key to activate the display.
On the display USER CODE will appear.

USER CODE
1   XX-XXXXXX

If you are registered as user, enter your code.
If timedelay is not programmed on the display OPEN will appear
Turn the handle and open the door.

OPEN

If a wrong or an invalid code is entered on the display WRONG CODE will appear.

WRONG CODE

OPENING MANAGER

Press any key to activate the display.
On the display USER CODE will appear.

USER CODE
1   XX-XXXXXX

If you are registered as manager, press ➡ and enter the
6-digits managercode

MANAGER CODE
1   XX-XXXXXX

If timedelay is not programmed on the display OPEN will appear
Turn the handle and open the door.

OPEN

If a wrong or an invalid code is entered on the display WRONG CODE will appear.

WRONG CODE

M-LOCKS BV
Vlijtstraat 40
NL-7005 BN Doetinchem

1

Tel: +31 (0)314 376 876
Fax: +31 (0)314 376 878
www.m-locks.com

CHANGE MANAGER CODE

Press any key to activate the display.
On the display USER CODE will appear.

```
┌────────────────────────────┐
│         USER CODE          │
│   1      XX-XXXXXX         │
└────────────────────────────┘
```

Press the key ✔ to enter the main menu.
On the display will appear:

```
┌────────────────────────────┐
│        MASTER MENU         │
│   1=     XXXXXXXX          │
└────────────────────────────┘
```

Press the key ➡ (2x) until you enter the menu Change Code

```
┌────────────────────────────┐
│        CHANGE CODE         │
└────────────────────────────┘
```

Then confirm with key ✔

```
┌────────────────────────────┐
│      CHANGE MANAGER        │
│           CODE             │
└────────────────────────────┘
```

Press key ➡ once and select Change Manager code.
Then confirm with key ✔

```
┌────────────────────────────┐
│         OLD CODE           │
│          XXXXXX            │
└────────────────────────────┘
```

Enter old code (when known), then enter new 6-digit code and confirm once more. When everything is correct, following message will show on display:

```
┌────────────────────────────┐
│      OPERATION DONE        │
└────────────────────────────┘
```

Press the key ➡ several times until EXIT will show on display. Confirm with key ✔ . Without pressing any key, the display will automatically be turned off after 20 seconds.

CHANGE USER CODE

Press any key to activate the display.
On the display USER CODE will appear.

```
┌────────────────────────────┐
│         USER CODE          │
│   1      XX-XXXXXX         │
└────────────────────────────┘
```

Press the key ✔ to enter the main menu.
On the display will appear:

```
┌────────────────────────────┐
│        MASTER MENU         │
│   1=     XXXXXXXX          │
└────────────────────────────┘
```

Press the key ➡ (2x) until you enter the menu Code Change.

```
┌────────────────────────────┐
│        CHANGE CODE         │
└────────────────────────────┘
```

Confirm with key ✔

```
┌────────────────────────────┐
│       CHANGE USER          │
│           CODE             │
└────────────────────────────┘
```

M-LOCKS BV
Vlijtstraat 40
NL-7005 BN Doetinchem   2

Tel: +31 (0)314 376 876
Fax: +31 (0)314 376 878
www.m-locks.com

Press key ✔ to change user code
The display will show OLD CODE

```
OLD CODE
XX-XXXXXX
```

Enter old code (when known), then enter new 6-digit code and confirm once more. When everything is correct, following message will show on display:

```
OPERATION DONE
```

Press the key ➡ several times until EXIT will show on display. Confirm with key ✔ Without pressing any key, the display will automatically be turned off after 20 seconds.

MANAGEMENT USER

Press any key to activate the display.
On the display USER CODE will appear.

```
USER CODE
1     XX-XXXXXX
```

Press the key ✔ to enter the main menu.
On the display will appear:

```
MASTER MENU
1=     XXXXXXXX
```

Press key ➡ to enter the MANAGER MENU

```
MANAGER MENU
1=     XXXXXXXX
```

Enter the 6-digit Manager code, then display will show:

```
USERS
MANAGEMENT
```

Confirm with key ✔ to enter the menu. The display will show an overview of active users.

```
02 03 04 05 06 07
V  _  _  _  _   X
```

Note:
V = Active user
_ = Free position
X = Blocked user (occupied position)

Enter the ID-number that you want to manage. The cursor will move to the right position (visible by the blinking cursor)
e.g. ID-02

```
02 03 04 05 06 07
■  _  _  _  _   X
```

Confirm with key ✔

```
02                 _   t1
    Install?
```

In case you wish to install ID-number 02, confirm with key ✔

In case you wish to block or delete the position, proceed with key ➡ and confirm this action with key ✔

Enter the new 6-digit code, and confirm this code once more.

```
NEW CODE
```

When everything is correct, following message will show on display:

```
OPERATION DONE
```

You will enter the USER Overview

```
02 03 04 05 06 07
V  _  _  _  _  X
```

Press the key ➡ several times until EXIT will show on the display. Confirm with key ✔ Without pressing any key, the display will automatically be turned off after 20 seconds.

M-LOCKS BV
Vlijtstraat 40
NL-7005 BN Doetinchem

4

Tel: +31 (0)314 376 876
Fax: +31 (0)314 376 878
www.m-locks.com